



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

Release Letter

Products:	<i>H.264 Firmware for CPP4 HD/MP cameras</i>
Version:	<i>6.40.0240</i>

This letter contains latest information about the above mentioned firmware version.

1 General

This firmware release is a feature release based on FW 6.32.0111.
It is an upgrade for CPP4 based cameras only.

This release introduces a set of security features and major improvements on bit rate optimization.

Changes since last release FW 6.32.0111 are marked in [blue](#).

Note:

Due to an internal file system being introduced since firmware 6.1x and architectural changes thereof, an upgrade to firmware 6.20 and higher is only possible from firmware 6.1x versions or higher. Cameras with previous firmware versions below 6.1x first need to upgrade to firmware 6.1x.



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

2 Applicable products:

- AUTODOME IP 4000 HD
- AUTODOME IP 5000 HD
- AUTODOME IP 5000 IR
- AUTODOME IP 7000 series
- DINION HD 1080p
- DINION HD 1080p HDR
- DINION HD 720p
- DINION imager 9000 HD
- DINION IP bullet 4000
- DINION IP bullet 5000
- DINION IP 4000 HD
- DINION IP 5000 HD
- DINION IP 5000 MP
- DINION IP starlight 7000 HD
- EXTEGRA IP dynamic 9000
- EXTEGRA IP starlight 9000
- FLEXIDOME corner 9000 MP
- FLEXIDOME HD 1080p
- FLEXIDOME HD 1080p HDR
- FLEXIDOME HD 720p
- Vandal-proof FLEXIDOME HD 1080p
- Vandal-proof FLEXIDOME HD 1080p HDR
- Vandal-proof FLEXIDOME HD 720p
- FLEXIDOME IP panoramic 5000
- FLEXIDOME IP indoor 5000 HD
- FLEXIDOME IP indoor 5000 MP
- FLEXIDOME IP indoor 4000 HD
- FLEXIDOME IP indoor 4000 IR
- FLEXIDOME IP outdoor 4000 HD
- FLEXIDOME IP outdoor 4000 IR
- FLEXIDOME IP micro 5000 HD
- FLEXIDOME IP micro 5000 MP
- FLEXIDOME IP outdoor 5000 HD
- FLEXIDOME IP outdoor 5000 MP
- FLEXIDOME IP micro 2000 HD
- FLEXIDOME IP micro 2000 IP
- IP bullet 4000 HD
- IP bullet 5000 HD
- IP micro 2000
- IP micro 2000 HD
- MIC IP dynamic 7000
- MIC IP starlight 7000
- TINYON IP 2000 family



From ST-VS/MKP1	Product Management	Nuremberg 27.07.2017
--------------------	--------------------	-------------------------

Note:

All CPP4 devices incorporate a Trusted Platform Module (TPM) with own firmware. This TPM hardware and firmware have been enhanced over time to allow for additional security features. Due to security reasons, the firmware or functionality of the TPM cannot be altered in the field. Thus, not all new security features become available on devices with older TPM hardware or firmware revisions.

Note:

Since firmware version 6.30 all cameras are prepared to receive a unique Bosch certificate during production, assigned and enrolled by Escrypt LRA. These certificates prove that every device is an original Bosch-manufactured and untampered unit. Escrypt is a Bosch-owned company, providing a public certificate authority (CA). Enrollment of the certificates in production is asynchronous to this firmware release.



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

3 New Features

Intelligent Streaming

- Intelligent Streaming is a combination of features and functions to optimize bitrate consumption of recorded video. It benefits from improved noise reduction in still areas of the image, an average noise level communicated to the encoder, larger GOP size, strong use of prediction in case of B slices, and dynamic tuning of quantization parameters (QP) in the encoder.
- The strength of the bitrate optimization can be set via 5 levels. Savings can be up to 80% but are strongly scene-dependent.

Security

- Password enforcement
 - New cameras with this firmware installed will only become operable after the password for the administration level (user "service") has been assigned.
 - Other users "user" and "live" will only become accessible after the administrator assigned passwords to them.
 - Cameras which are updated to this firmware from a version lower than 6.40 will not change their behaviour and remain at their former protection level unless reset to factory defaults.
- Signed firmware file enforcement
Only Bosch-signed firmware will be accepted by the camera without compromises. A downgrade to a non-signed firmware is not possible anymore.
- Data encryption on iSCSI storages
 - The payload on an iSCSI drive is encrypted using a symmetric XTS encryption scheme (block encryption).
 - The camera uses a number of public keys to asymmetrically encrypt the XTS key for multiple receivers. These public keys are maintained in the certificate store via certificates. Usage can be defined as for „recording1“ and/or „recording2“.
 - Payload encryption is possible on SD cards as well as on external iSCSI storage.
 - A client that shall be allowed to replay this footage must have its cert/key registered and activated.
 - The Video Recording Manager (VRM) may also be a receiver to decrypt the payload data for replay.
- SRTP payload encryption for live and replay
SRTP provides payload encryption of UDP streams via TLS, similar to what HTTPS does by using TLS for TCP streams. Also encrypted multicast connections are possible.



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

- **SNMPv3 support**
 - New alternative SNMP support provides encryption and authentication. This new service will provide pure MIB-II access.
 - Legacy functions, like NTCIP support or mapping of dedicated RCP commands to SNMP Enterprise MIB nodes, are only provided with existing SNMPv1 implementation.
- **Certificate revocation list (CRL) support**
- **To improve usability and provide a more compact overview, the web user interface for the certificate store has been updated. It now allows direct tagging of certificates for usages. The former split into two areas (Files and Usage) is removed.**
- **Stronger encryption and password protection for configuration file**
 - The configuration file is encrypted and password-protected before download.
 - The user as the owner of this configuration file is prompted for the password.
 - The password is required when the configuration file is uploaded to a camera.
 - The configuration file is encrypted using standard mechanisms but not intended to be opened or modified by the user, thus the encryption key itself is kept internal and not exposed.
- **Stronger encryption for maintenance log file**
The maintenance log file as being used in tech support cases is encrypted with a Bosch public key. Only tech support staff is authorized to decrypt and open the file.
- **The minimum TLS version can be defined, e.g. to avoid vulnerabilities from TLS 1.0 and 1.1.**
- **The Telnet console has been completely removed and is substituted by a new logging facility providing:**
 - A more structured output including timestamp, severity and module sources
 - Search and filtering for specific events via web user interface
 - Direct output to a syslog server
 - Configuration to produce similar “debug” printouts for tech support as previously
- **Consolidation of running services, visualized on new page “Network Services”.**
Only those services (HTTP, HTTPS, RTSP, RCP, iSCSI, NTP, discovery, ONVIF discovery) are running which are required for activated functionality. All other services (FTP, SNMP, UPnP, GB/T 28181) and their respective ports are deactivated.
- **The password unlock functionality (support recovery option) can be disabled.**
- **CHAVE cameras**
 - Multiple trusted issuers are now allowed for client certificate authentication.
 - An option to not wipe the SXI certificate when a factory default is issued has been added.



From
ST-VS/MKP1

Product Management

Nuremberg
27.07.2017

Imaging

- Improved noise filtering in still scenes.

VCA

For details on VCA 6.40 please refer to the separate release notes of Essential Video Analytics or Intelligent Video Analytics.

ONVIF

- ONVIF manual iris and focus controls added.
- Feature coverage of the ONVIF metadata stream has been extended to include e.g. object classes, object shape polygons, faces, flame and smoke detection info.
- Profile G support
 - Recording start and control has been added.
 - Recording search and replay functionality has been added.
 - Tested with ONVIF Device Test Tool 16.07 SR2 rev. 617.

Miscellaneous

- SMTP port is now configurable via web interface.
- Multipathing support for storage devices.
- User name from certificate for EAP-TLS is used as EAP identity, if provided.
- Dynamically colored privacy masks, depending on surrounding video added. This can be used to not distract the operator due to intense color, e.g. white privacy mask in night scene.
- Cameras can connect to the CBS Remote Portal installer service.
- New illuminators for MIC 7000 are supported.
- An event playback button has been added to the Live page to allow a quick playback of the last event in case there was an incident and the camera was connected remotely to check what happened instead of checking live and then go to the playback page.
- Default device date is set to firmware build time in case of invalid RTC time to avoid lock-out in case of certificate-based authentication.
- Dropbox API has been updated. The API used before was going obsolete on June 28th, 2017.



From
ST-VS/MKP1

Product Management

Nuremberg
27.07.2017

4 Changes

- [Compass indicator moved towards center to appear also in 4:3 resolutions.](#)
- [Installation Code has been enhanced with a block for crypto-coprocessor version indicators. The length of the Installation Code has been extended to 48 digits instead of only 44 digits.](#)
- [Improved certificate parser to support more attributes used e.g. by various mail providers.](#)

5 System Requirements

- Web Browsers:
 - Microsoft Internet Explorer 11 or higher
 - Mozilla Firefox
- DirectX 11
- [MPEG-ActiveX 6.11 or newer](#)
- [Configuration Manager 5.50 or newer](#)



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

6 Restrictions; Known Issues

User Interface

- If UAC is set to default in Windows 7, no snapshot or recording via LIVEPAGE is possible.
- Video and audio may be asynchronous during replay via Web page.
- If a VCA configuration using a rule engine is switched to a VCA configuration without using a rule engine, e.g. MOTION+ or IVA default configuration, the saved configuration is invalid. Forensic search with this configuration may lead to undesired search results.
- In rare cases it may happen that no recordings can be found on PC with Windows XP SP2 and IE6. Internet Explorer may stay in status 'connecting on replay page'. An update of Internet Explorer is recommended.
- In Firefox, no audio is audible on the Audio Settings page.
- Opera mini for mobile devices cannot work in Intranets because it gets all pages through an opera proxy in the Internet. If there is no Internet connection no content is provided.
- When changing GUI language, the browser cache may have to be deleted and the web browser be reloaded before the language will be selected correctly.
- Google Chrome requires a plug-in for displaying TIFF images to properly show the reference image.
- IE10 by default does not allow snapshots or recording from the LIVEPAGE on local hard disk until one of the following actions is performed:
 - - uncheck the box "Enable Protected Mode" in internet options/security
 - - add the device's IP range to "Local intranet" zone
 - - add the device's IP address to the trusted sites
 - - start IE as administrator
- If an intranet site is opened, IE10 automatically runs in compatibility mode. This leads to a misbehaviour that no timeline is shown on the PLAYBACK page. Therefore the function "Display intranet sites in Compatibility View" must be disabled.
- With HTTPS connection in MS IE and VideoSDK 5.71 installed, swapping between stream 1 and 2 may cause the watermarking icon for stream 2 disappear. This may happen only for TCP video streams with infinite I-frame distance and B-frames on. A fix is available since VideoSDK 5.71 MR1.
- Upgrading the firmware to version 6.10 may require clearing the Web browser cache to have the new user interface style appear.
- [Fluent decoding of buffered .mp4 video from camera is strongly dependent on the browser, Jerky video may occur, e.g. with Mozilla Firefox 52.0, which is not a camera malfunction.](#)



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

Encoding

- Only H.264 Main Profile using CABAC is supported. CAVLC is not supported.
- JPEG always has HD 1080p format, although stream 1 could be set to SD (480p).
- Frame rates in low light mode might vary and cause bit rate control to produce higher bit rates than set as maximum.
- Aspect ratios 16:9 and 4:3 are not combinable. Aspect ratio from stream 1 will lead.
- With GOP structure set to IBP and IBBP the I-frame distance may not exactly correspond with the set value.
- For stream setting "Dual ROI" the maximum resolution of stream 2 is 288p regardless of a higher resolution selected in the encoder profile.
- If bit rate is already reaching maximum level due to image content to be encoded, encoder quality regions with setting "object" cannot be improved for quality anymore and differences will gradually be reduced.

Security

- When using certificates for mutual authentication, it must be ensured that the camera uses a solid and trusted time base. In case the time differs too much from the actual time, a client might be locked out. Then, only a factory default will recover access to the camera.
- Underscore character ("_") is not allowed in common name in certificates.
- Excessive signing, e.g. due to very short video authentication signing interval, may have an impact on TLS connection setup.
- Client authentication is not working using Microsoft Edge as the browser does not send any certificate for client authentication, so the camera has nothing to authenticate.

Network

- QoS values are set according to group Video/Audio/Control for UDP packets, but for TCP packets, only the QoS value for Video is inserted.
- IP addresses 172.20.1.0/30 which include 172.20.1.0 to 172.20.1.3 are reserved for internal communication and must not be used as device addresses. Products without internal communication ignore this restriction and allow the use of this range.



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

IVA

- IVA and flow need at least 12.5 frames per second video input frame rate. If IVA or Flow are configured, minimum frame rate of 12.5 must be set in ALC mode.
- There is only one configuration for IVA. When analysis type is changed, e.g. from IVA to IVA Flow, the former configuration is lost. Due to this, it is not possible to change the analysis type in a VCA profile switch.
- Due to a limitation of the script language that is used in the background, the delay timer for event-triggered VCA starts immediately when the configuration is set. A trigger event during this period does not restart the timer. Once the timer has elapsed, operation is as desired.
- On devices with VCA FPGA an outgoing IPv6 connection fails when device is initiator, e.g. trying to resolve a time server domain name,
- For 720p cameras, when switched to 1.3MP application mode, IVA does not work. As a result also iAE does not work, as IVA is needed for that. And therefore also User Mode "Intelligent AE" does not work optimally (it is using BLC).
- After firmware upgrade to version 6.10 the minimum object size seems being reset when editing 'motion in field' task. As a proposed workaround check minimum object size and correct value as applicable.
- "Too dark" alarm is not triggered under normal conditions due to the cameras low-light capabilities.
-

MOTION+

- An alarm recording configured to be triggered by MOTION+ with masks may not be operational after reboot. Saving MOTION+ configuration without any changes recovers from that. Alternatively masks may not be used with MOTION+.



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

Recording

- LUN size for local recording via “Direct iSCSI” is limited to 2 TB.
- VRM version 2.12 or higher is required.
- In some cases formatting errors on external iSCSI drives may occur, which might need multiple tries to overcome.
- In rare cases it may happen that the owner of an iSCSI LUN is not displayed correctly. Recording is not affected, just previous owner remains displayed.
- If a device had primary and secondary recording running on SD card and is then added to a VRM system, the blocks used for primary recording will not be re-used, reducing the available recording space for the ANR recording. This can be solved by re-formatting the SD card.
- Throughput limit for simultaneous recording and local replay at 100% playback speed is:
 - maximum total recording bit rate of 7 Mbps for external iSCSI recording
 - maximum total recording bit rate of 10 Mbps for SD card recording, depending on SD card performance
- SD card recording performance is highly dependent on the speed (class) and performance of the SD card.
- With I-frame-only recording and audio also enabled for recording, audio will be fragmented or not audible during replay. Please disable audio recording in case of I-frame-only recording.
- Numbering of the recorded files on the replay page is not always contiguous. If snippets across block borders belong together, like pre-alarm and alarm recording, the snippets become logically united and only the lower file number is presented in the list.
- SDXC cards are formatted to FAT32 file system and not using the exFAT file system as being mandatory for SDXC standard compliance but fully recognized and accessible. The maximum size of 2TB is also supported with FAT32, once SD cards of that size might become available. FAT32 also increases portability to other than Windows platforms.
- If a local media is exchanged, existing former recordings are only discovered after rebooting the device.
- Physically removing the local storage media while recording causes the device to reboot. Recording must be stopped before removal.
- Changing audio format while audio is being recorded may cause unknown behaviour of the device and must be avoided.
- 5MP and larger JPEG streaming via RTSP is only possible with decoders supporting the ONVIF extensions.

JPEG streaming via RTSP is based on RFC 2435. This RFC only allows for a maximum JPEG size of 2048 by 2048.

With ONVIF, the original, larger JPEG headers can also be transmitted via RTP header extensions. Unfortunately, this only works with decoders using these extensions, i.e. it does not work with a standard VLC.
- After modifying account settings, e.g. FTP server address, to get the changes applied either switching posting off and on or restarting the device is required.



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

- The storage system indicator status must be ignored during formatting of an SD card.
- Forcing the camera into an overload situation may cause undesired behaviour and in worst cases even recording gaps. It should always be ensured that the CPU load is not consistently around or at its maximum. This can be achieved by adapting encoder settings or avoiding too many tasks, e.g. client sessions, in parallel.
- Sporadically occurring incorrect time zone info in recording packets may lead to gaps displayed in the playback timeline. The video footage within the gap cannot be replayed but becomes accessible via exporting the affected period. This may happen with firmware 6.32 below built 111.

Export

- FTP exported files which include audio in a format other than AAC must be renamed from .mp4 to .m4a to allow correct playback in QuickTime.
- With JPEG Posting active when device is booting, the first posted JPEG image may be a no-cam logo.
- FTP posting with resolution 1080p delivers JPEG with size of 1920x1072 pixels due to 16 pixel macroblock boundary of the JPEG encoder.
- If FTP export files contain only a few frames some players might not correctly replay such a file, or the replay is too quick to recognize something. The exported file is not corrupt though it might seem so.
- Files exported using continuous FTP backup for Rec. 2 where stream 2 is set to I-frames only mode contain wrong timing information and play back too fast.
- FTP export file size is always 100 MB if resolution change occurred in exported time span.
- Getting the file list from Dropbox may fail if there are too many objects (files and folders). Limit is approximately higher than 500 objects but also dependent on file name length etc.

ONVIF conformance

- When using GetPresets command preset names are not set for scene1 to scene6.



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

DIVAR IP 2000 / 5000

- Due to its improved security features, firmware 6.40 is not fully backward compatible with DIVAR IP 2000 and DIVAR IP 5000. Upgrading cameras to FW 6.40 without to-be-released firmware upgrades for DIVAR IP 2000 and DIVAR IP 5000 may cause configuration problems and possibly stop recording.

DIVAR hybrid / network

- Cameras running FW 6.40 are only compatible with DIVAR network / hybrid FW 1.2.1 and higher. With earlier DIVAR network / hybrid firmware versions, the I-frame distance needs to be adapted to 30 or less.

Fixed cameras

- In case if there is no image displayed after upgrade to new firmware, please re-power the camera. Applicable cameras :
 - FLEXIDOME IP INDOOR 5000
 - FLEXIDOME IP OUTDOOR 5000
 - FLEXIDOME IP bullet 5000
 - FLEXIDOME IP INDOOR 4000
 - FLEXIDOME IP OUTDOOR 4000
 - DINION IP 4000 HD
 - DINION IP BULLET 4000 HD
 - DINION IP 5000 HD
 - DINION IP BULLET 5000 HD
 - DINION IP 7000 HD
- If analogue video output is switched on, the frame rate of the first stream is limited to 15 fps.
- With analogue output enabled and image rotated, the stream 2 resolution is limited to 720x720 pixels maximum.
- On DINION IP starlight 7000 HD, running stream 1 with 720p60, stream 2 is limited to SD resolution running at max. 30 fps.
- Due to the feature enrichment, panoramic and 5MP cameras needed some adaptations to free enough memory to remain functional:
 - The maximum JPEG quality for hardware encoding has been slightly reduced from 80 to 75. Software-encoded JPEGs use a quality of 100.
 - Maximum I-frame distance remains at 60 fps while other CPP4 cameras have I-frame distance extended to 255 for full utilization of Intelligent Streaming.
 - Camera name stamping rows are limited to 2 instead of 6.



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

Dome cameras

- Autopan starts outside of defined range if orientation is set to “Inverted”.
- Tilt up limit is treated as lower tilt limit if orientation is set to “Inverted”.
- For VG5, when Fast Address was changed a reboot is required to activate it.
- In AUTODOMEs, blanked sector may trigger a “too dark” alarm.
- On AUTODOMEs, privacy masking does not cover the complete configured area if privacy mask is placed too close to the edge of a scene. Move the target position to the center of the scene before creating a privacy mask.
- If LIVEPAGE is refreshed during recording of Tour A/B on AUTODOMEs the button “Stop display” will falsely display “Start recording” but still continue tour recording.
- After a firmware upload it may happen that the Privacy Masks and settings from Installer Menu are set to default. Make sure to check if Privacy Masks and Installer Menu settings are still valid after uploading new firmware.
- Some online help files describe a tracking icon which is not visible, documentation obsolete.
- For optimal image performance the user is advised not to turn off contrast enhancement during normal camera operation.
- To improve Recorded (Guard) tour playback accuracy, Bosch recommends users record tours using the User Interface (UI) instead of using a keyboard. In the event that the Recorded (Guard) tour loses position accuracy during playback, users should re-home the camera using the “Find home” button on the Live page.
- Since firmware 5.90 the camera module in AUTODOME 7000 HD receives a different setting that is persistent over a firmware downgrade as older firmware doesn't know of this parameter to revert it.

If it is required to downgrade a RCP CGI command needs to be applied before or after the downgrade:

http://<ipaddress>/rcp.xml?command=0x09a5&type=P_OCTET&direction=WRITE&protocol=TCP&payload=0x80000405300381010424560000ff&num=1

- MIC 7000 orientation can be switched between normal and canted.
- When the user changes orientation from normal/canted to inverted (or vice versa), MIC 7000 will tilt itself up and over so that the visor and wiper are on top. If there is an attached illuminator this would result in the illuminator hitting the MIC's body. To avoid this, MIC 7000 will not allow an orientation change while the illuminator is attached. A warning message with “Yes/No” selection will be displayed when the user clicks the orientation radio button and the MIC has an illuminator.
- On AUTODOME 7000 and MIC 7000 “HDR” can be selected in the preposition mapping but has no effect as it is not supported in these models.
- NTCIP requires to have the SNMP port enabled to become functional. As the SNMP port, amongst others, has been closed by default if not needed due to security improvements, it must be re-enabled to allow NTCIP to work.
- **Scene/VCA profile may not be correctly restored, causing the Sketch button to be disabled.**



From
ST-VS/MKP1

Product Management

Nuremberg
27.07.2017

Miscellaneous

- The camera date/time will be set to default (Year 2000) after power loss exceeding the buffer period. It is important to ensure that the date/time is correct for recording. An incorrect date/time setting could prevent from correct recording.
- After firmware upload while daylight saving time checkbox is activated the time zone must be adjusted.
- After reboot, the system time re-synchronisation may be delayed up to 9 seconds for SNTP respectively up to 14 seconds for time server protocol.
- A printout was added to telnet when sending an e-mail failed.
A more detailed printout was added for the three error cases 'could not connect to server', 'authentication failed' and 'recipient not accepted'.
- AAC audio timestamps for UDP live video streams as well as for recording streams are based on 90 kHz instead of 16 kHz to ensure compatibility with Video SDK.
AAC audio timestamps for TCP live video streams are based on the standard 16 kHz timestamps. Standard players should connect to live video with AAC audio using TCP.
- After changing the selectable camera mode via alarm input the switch back to a previous mode doesn't work anymore.
- Firmware upload stops recording when it fails or is terminated.
- After downgrade configuration integrity cannot be ensured and settings need to be checked or re-configured.
- When a configuration file is loaded to an incompatible camera, e.g. a configuration file from a HD camera loaded onto a VGA camera, encoder settings might become invalid and need to be re-configured.
- [Uploading a configuration file from a different camera platform may result in unpredictable behaviour.](#)
- If it shall be checked if the image is not frozen, use milliseconds timestamp to verify.
- Intelligent Defog default is OFF under "Low bitrate" scene mode.
- When combining CPU-intensive functions like e.g. encryption, watermarking, or dual recording, with high quality and high frame rate encoder settings, tuning of encoder profile settings might be required to avoid overload situations.
- No time change is allowed during the time when the "hour is repeated".
- Maintenance log file creation and download requires some time, though there is no progress indication, and needs to be waited for completion.
- [Millisecond stamping on 60 fps cameras is refreshed with 30 Hz only, updating only every second frame.](#)
- [JPEGs with VCA overlay are not fully synchronized. Shapes might be slightly off.](#)

Please check the respective release letter of a camera for further device-specific restrictions.



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

7 Previous Revisions

7.1 New Features with FW 6.32.0111

Imaging

- Lens settings Near Focus Limits for day and night have been added.
- Sectors in dome cameras can be more flexible set to 4, 8, 12 or 16 (default).

Security

- Strengthened password policy:
 - New passwords must now be a minimum of 8 characters including special characters.
 - Passwords are continuously demanded; message cannot be hidden anymore.
- For full support of HSTS, an option “HSTS plus HTTP redirection” has been added.
- Fallback to TLS 1.0 can be disabled.

VCA

- JPEG with VCA overlay is now also available in full screen view.

For details on VCA 6.30 please refer to the release notes of Essential Video Analytics or Intelligent Video Analytics.

Miscellaneous

- Improved user interface for 802.1x settings. Interface shows an EAP-MD5 password field and lists the EAP-TLS certificates with a link to the certificate store.
- Security coprocessor (TPM) version is listed in system overview.
- Aux and preposition widgets on Live page can be completely disabled in Web appearance settings.
- New capability “cluster group” has been introduced. MIC integrators can get the audio back channel capability on VIDEOJET connect 7000 from this cluster group.

AUTODOME 7000

- Mosaic privacy masks are supported in AUTODOME IP 7000 series.



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

7.2 Changes with FW 6.32.0111

- Limited frame rate stream capability names are presenting the frame rate as “skip” value, which is used as divisor in relation to the base frame rate.
A value “skip 5” results e.g. in 12 fps if base frame rate is set to 60 fps, or in 5 fps if base frame rate is set to 25 fps.
- In preparation for ONVIF Profile Q support, planned for next major firmware release, the default setting for Automatic IPv4 address assignment has changed from “On” to “On plus Link-Local”, a setting that had already been in the option list before.
Though this might seem a small change, it may have an impact:
The former default IP address 192.168.0.1 will virtually become obsolete.
Instead, the camera will assign itself an auto-IP address out of the range 169.254.1.0 to 169.254.254.255 as long as there is no other IP address assigned by a DHCP server.
(https://en.wikipedia.org/wiki/Link-local_address)
The advantage is that there are no more duplicate IP addresses, which is considered prohibited in a network.
- VCA overlays are drawn after scaling to improve visibility.
- An issue has been fixed where the maintenance log could not be downloaded.
- An issue has been fixed where the wrong SD card recording status was displayed.
- A security leak, which allowed to extract critical data from the device, has been fixed.
- A problem with incorrect time zone info in recording packets causing gaps in timeline has been fixed.



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

7.3 *New Features with FW 6.30.0140*

Imaging

- A 1.3 MP application variant is now selectable for DINION IP bullet 4000 cameras.

Security

- The user management has been extended to allow free assignment of usernames. Each user can be assigned a user group representing live, user, or service level.
- New user management system allows to dynamically create a user for whom the password can be treated as token. Also timeout before user account expires is possible.
- Token-based authentication implemented to allow user management based on communication with Microsoft Active Directory Federation Services.
- Secure FTP connection (FTP over TLS) is implemented.
- ICMP redirect messages are not accepted anymore by default. Acceptance can be re-enabled via RCP+ command, if needed.
- Video authentication is now also possible on RTSP streaming. It can be enabled with CGI parameter 'auth=1' which requests picture info packets (payload type 97).

Recording

- Recording to iSCSI now supports LUN size up to 64 TB.
- A PTZ preposition can be stored in a recording profile, allowing to record only a 'region of interest' (ROI) of the full image.

ONVIF

- ONVIF encoder profile settings can be verified via http://<ipaddress>/onvif_encoder_profiles.
- Manual focus and iris control is now supported via ONVIF command.
- Tamper detection alarms are now forwarded to and included in ONVIF event services.



From
ST-VS/MKP1

Product Management

Nuremberg
27.07.2017

VCA

- Web page layout has been improved for better usability and larger video for configuration.
 - Video analytics now fully support 16 tasks in RCP+ and IVA Task Script Language.
 - JPEGs can now include VCA overlays in Live page, alarm e-mails and JPEG Posting. For JPEG snapshot a new query parameter 'VCAOverlay' can be added to the URL, e.g. <http://<ipaddress>/snap.jpg?VCAOverlay=1>.
 - Video can now be paused during VCA configuration.
 - Reference image is now stored as JPEG instead of TIFF for broader compatibility.
 - Tamper detection "too bright / too dark" was no more functional due to too high dynamic on our cameras.
To solve this issue, sliders for the brightness level have been added for manual adjustment.
- For details on VCA please refer to the release notes of Essential Video Analytics or Intelligent Video Analytics.

Miscellaneous

- HTML5 video tag is used to display a continuous MP4 video file from the camera on browsers not supporting NPAPI plug-ins (MPEG-ActiveX) like Firefox, Chrome and MS Edge.
- A "Links" section in the main navigation (blue top bar) has been added, leading to a DownloadStore page providing latest tools, apps and supportive software.
- Unicode characters are now also possible on all configuration strings.
- Time server IP address can be accepted to be overwritten by DHCP.
- Display of preposition widget on Live page can be configured.
- MIC washer has been added to preset mapping functions.

7.4 Changes with FW 6.30.0140

- "Image too noisy" is removed as it never occurs due to the high dynamic of image processing.
- Downscaled images 4CIF/CIF are now encoded as PAL resolution (704x576 resp. 352x288) when camera is set to 25/50 fps base frame rate.
- Fixed a potential recording issue which could cause recording to stop due to insufficient storage error handling under rare error conditions, like e.g. massive irregular network connection interrupts to storage system.
- Fixed an issue in ONVIF signaling of SD resolution.



From ST-VS/MKP1	Product Management	Nuremberg 27.07.2017
--------------------	--------------------	-------------------------

7.5 Changes with 6.22.0007

- Support of new camera modules in AUTODOME 7000 and MIC 7000, providing improved noise reduction.
- A high-resolution/limited-frame-rate capability has been introduced for stream 2 on various cameras.

7.6 Changes with 6.22.0007

- Writing to ONVIF MaxFrameRate is now possible to improve compatibility with clients not using encoding interval. Written values are presented in same format when read.

7.7 Changes with 6.21.0008

- An issue with increased noise and thereof increased bit rate from AUTODOME and MIC cameras has been fixed.
- Auto Focus accurateness on DINION IP bullet 4000 and DINION IP bullet 5000 has been improved.
- An issue with fragmented EAP-TLS transfer has been fixed, allowing support for Microsoft Windows NPS and RADIUS.
- An issue with ONVIF Analytics Service has been fixed.
- GUI translations and some embedded help files have been updated.
- An issue with analogue output flickering on DINION IP starlight 7000 and FLEXIDOME IP starlight 7000 in 1.3 MP mode has been fixed.
- Wrong wording on time protocol settings has been fixed.



From
ST-VS/MKP1

Product Management

Nuremberg
27.07.2017

7.8 New Features with 6.20.0089

Cameras

- Support for DINION IP bullet 4000 and DINION IP bullet 5000.
- Dome and AUX functions can be mapped to presets.
- MIC-7000 audio back-channel support towards VJC-7000 audio output on LIVE page.

Security

- Support of TLS 1.2 with updated cypher suites including AES 256 encryption.
- Device access security has been improved by:
 - Implementation of signed time synchronization
 - Signature-protected password unlock procedure
 - Telnet over HTML5 web sockets in browser, using secure TLS connection
 - Throttling of wrong password entries
 - Urging user towards setting a device password, strength meter provided
- Firmware, which is signed with a private certificate, is authenticated before transfer to Flash to ensure a secure firmware upload.
- Certificate handling has been enhanced by:
 - Auto-generation of self-signed certificates for SSL
 - User-defined creation of self-signed certificates
 - Possible upload of certificates with encrypted private keys
 - Improved recorded video authentication without PKI required
 - Storage and retrieval of certificate in recording for verifying signed video
- Web GUI security has been improved to prevent Cross-Site-Scripting in Browser.
- Use of secure connections can be advertised via support of HSTS.



From
ST-VS/MKP1

Product Management

Nuremberg
27.07.2017

7.9 Changes with 6.20.0089

- 56-bit encryption disabled for secure connections to increase minimum security level.
- Telnet service (system console) is now disabled by default.
- DHCP option 12 has been changed to send 'Renew' message including the camera name as hostname.

7.10 New Features with 6.11.0021

- Adding improved AF speed for AVF cameras.

7.11 Changes with 6.11.0021

- Adding small improvements and error corrections.
- ONVIF analytics capabilities have been corrected for dome cameras.
- Replay not working in BVC and BVMS clients for negative time zones has been fixed.



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

7.12 New Features with 6.10.0129

New Graphical User Interface

- Light and friendly Web browser interface following the Bosch Security Systems style guide for software interfaces.
- Usability improvements due to clearer structure and elements.
- Live preview during configuration wherever possible due to space.
- Tours re-arranged onto single page and scheduler for preset tour and alarm rules added for moving cameras.
- Encoder quality regions can be configured on moving cameras' preset positions with up to 8 regions.
- Video export format can be preselected from Bosch format including metadata and generic MP4 format on LIVE page.

Imaging Enhancements

- Digital Zoom mode added to lens settings page.
- Setting migration keeps all the previous imaging settings after camera upgraded to new firmware. Please note: This is only applicable after firmware 6.10.

Security Enhancements

- Certificate Store for management and assignment of client and server side certificates.
- Preparation for Public Key Infrastructure (PKI), enabled via special license, has been added.
- 56-Bit DES cipher suite is disabled for TLS connection.

IVA Enhancements

- Object classification of object types "upright person", "bike", "car", "truck" replaces head detection.
- Geolocation allows setting a camera's global coordinates. The position of the tracked objects in the respective coordinate system is added to metadata. Camera viewers can show the tracked objects on a map.
- Usability improvements allow for easier calibration and easier drawing of elements and masks.
- MOTION+ configuration has been reworked. Eight MOTION+ alarm fields with up to 16 nodes can now be set. Areas can be removed from processing via VCA masks, which will then suppress metadata generation in these areas.

Note: For details and complete overview refer to release notes of IVA 6.10.



From

ST-VS/MKP1

Product Management

Nuremberg

27.07.2017

ONVIF Enhancements

- IVA events can be received via ONVIF messages.
- Overlay metadata can be received in ONVIF XML format.
- AUX commands can be sent via ONVIF messages.
- Special functions like IR Correction, Visible White Light and Anti-Fog for MIC 7000 can be sent via ONVIF messages.
- Intelligent Tracking for AUTODOME and MIC can be enabled via ONVIF messages.
- Conformance was tested using recent ONVIF test tool 14.12.

Miscellaneous

- Missing time zones added for Caracas, Newfoundland, Kathmandu, Yangon, Samoa and Kiribati Island.
- 3rd party protocol support can be enabled via special license, showing specific menu when license is installed.
- Internal storage can be disabled and hidden via special license for certain LATAM countries. This license can only be cleared via technical service and support.
- An additional area in the flash memory, holding a file system to store specific files or data, has been implemented. This area can hold such like the enhanced Chinese character table or the FPGA image for IVA cameras running in 5:4 setup, certificates or configuration data. With FW 6.10 necessary files can be installed by uploading a supplementary firmware file. For successive firmware versions the sections will be recombined.
- Besides normal POE+ power signalling, with a special license installed the available power can be signalled proprietarily. Signalled power can be configured manually when license is installed.
- A customer logo up to 128x128 pixels with a depth of 256 colors can be uploaded as BMP file to be displayed in the camera name block. Options for placement are left, right or logo only.

7.13 Changes with 6.10.0129

- IPv6 operational improvements, e.g. netmask extended to 64 bit.
- Reference image is deleted when device is set to factory default.
- Improved robustness of encoding DSP.
- Fix for JPEG resolution handling on AUTODOME IP 7000.
- Fix for recording status while pre-alarm recording in RAM.